

VARIABLE CLOCK CONFIGURATION FOR SWITCHED OP-AMP CIRCUITS

5 Background of the Invention:

Field of the Invention:

The invention relates to a circuit configuration in switched op-amp technology and to a method for clocking successive operational amplifier stages constructed in switched op-amp technology.

The switched op-amp technology has developed from the switched capacitor technology to be able to take into account the requirement for ever-lower supply voltages. The switched op-amp technology is used in the construction of filters and converters and is especially suitable for fields of application in which low power consumption is of importance. The field includes, for example, applications in the mobile radio field in which the load on the battery must be kept as low as possible.

Whereas the capacitors are switched on and off by clocked switches in the switched capacitor technology, the operational amplifiers are also switched on and off by a switching clock signal in the switched op-amp technology. Such a configuration results in considerable power saving.

In the prior art, two successive operational amplifier stages are operated with opposite clock pulses. A prior art non-overlapping two-phase clock is used for the clocking.

- 5 Accordingly, the operational amplifiers of the successive stages are never active at the same time. However, the clock configuration is selected such that each operational amplifier is switched on for approximately 50%.

Summary of the Invention:

It is accordingly an object of the invention to provide a variable clock configuration for switched op-amp circuits and a method for clocking successive operational amplifier stages constructed in switched op-amp technology, that overcomes the hereinafore-mentioned disadvantages of the heretofore-known devices and methods of this general type and that achieves a further reduction in the power consumption of switched op-amp circuits.

- 20 With the foregoing and other objects in view, there is provided, in accordance with the invention, a circuit configuration in switched op-amp technology including at least one switchable operational amplifier having an input and an output, at least one sampling capacitor connected to the
- 25 input, at least one integrating capacitor connected to the input and to the output, a clock generator producing at least

two non-overlapping switching-clock signals each having switching-clock phases including an on-phase and an off-phase; and a phase-variance device varying the switching-clock phases in which the first and second switching-clock signals are in the off-phase. The phase-variance device is connected to the clock generator. The at least two non-overlapping switching-clock signals include a first switching-clock signal and a second switching-clock signal. The clock generator controls charging of the sampling capacitor with the first switching-clock signal and switching the operational amplifier on and off with the second switching-clock signal.

The circuit configuration in switched op-amp technology according to the invention includes at least one switchable operational amplifier, at least one sampling capacitor that can be connected to the input of the operational amplifier, and at least one integration capacitor disposed between the input and the output of the operational amplifier.

At least two non-overlapping switching-clock signals are generated for controlling the circuit configuration. As long as one of the two switching-clock signals is at 1, the sampling capacitor is charged up by the input signal. During the phase, the other one of the two switching-clock signals is at 0 and the operational amplifier is in its switched-off state. At the end of the sampling phase, all switching-clock

signals are in a common off-phase. The other one of the two switching-clock signals then changes to 1 and, thus, switches on the operational amplifier. During the integration-phase that now starts, the operational amplifier, as the active component, transfers the charge of the sampling capacitor connected to its input to the integration capacitor. At the end of the integration-phase, both switching-clock signals are again at 0.

The circuit configuration according to the invention has a device or means for varying the switching-clock phases in which all switching-clock signals are in the off-phase. The configuration makes it possible to stretch the switching-clock phases in which both switching-clock signals are at 0, at the cost of the on-phases. It is only necessary to ensure that the sampling capacitor can be completely charged up by the input signal during the on-phase of one switching-clock signal and that the operational amplifier can settle sufficiently for the charge to be transferred to the integration capacitor during the on-phase of the other switching-clock signal.

Thus, the common off-phase of the two switching-clock signals can be extended up to the limit predetermined by the transient response, making it possible to use the potential for power saving to its full extent. The invention is, thus, particularly suitable for use in mobile transceivers

(mobiles), mobile Internet devices (WAP technology) but also for medical use (hearing aids, pacemakers etc.) in which a long life of the batteries used is of importance.

5 In particular, the invention makes it possible to adapt the length of the on- and off-phases individually to the Q factor of the operational amplifiers used. To take into consideration the influence of process spreads in the manufacture, analog circuits must be dimensioned such that they still meet the required specification even with disadvantageous process effects. In many cases, therefore, the behavior of an analog circuit is better than specified by the manufacturer. If the transient response of the operational amplifier used is better than specified, the potential can be exploited for saving power using the invention.

In accordance with another feature of the invention, it is an advantage if each of the switching-clock phases in which all
20 switching-clock signals are in the off-phase is variable. Both the common off-phase that follows the on-phase of the first switching-clock signal and the common off-phase that follows the on-phase of the second switching-clock signal are extended. The process results in a uniform switching
25 configuration. However, it is also possible to make the off-phase following the on-phase of the first switching-clock

signal and the off-phase following the on-phase of the second switching-clock signal be different lengths.

As an alternative, in accordance with another feature of the invention, it is possible to vary only every second one of the switching-clock phases in which all switching-clock signals are in the off-phase. In such a solution, in each case only the off-phase following the on-phase of the first switching-clock signal is extended or in each case only the off-phase following the on-phase of the second switching-clock signal is extended. Thus, every second common off-phase is in each case extended.

It is an advantage, in accordance with an added feature of the invention, if the duration of the switching-clock phases in which all switching-clock signals are in the off-phase can be varied in dependence on the transient response of the operational amplifier. To achieve maximum power saving, the on-phase must be selected to be just long enough for the operational amplifier to be able to settle. Once the transient has ended, the operational amplifier can be switched off.

In accordance with an additional feature of the invention, the duration of the switching-clock phases in which all switching-clock signals are in the off-phase can be varied in dependence

on the switching speed of the transistors. Because an operational amplifier is made of individual transistors, the transient response of the operational amplifier is essentially determined by the switching speed of the transistors. Thus, the transistor switching speed is an easily detectable measure of the transient response of the operational amplifier. The switching speed of the transistors can be used directly for determining the duration of the common off-phases: The faster the switching of the transistors, the longer the common off-phase can be selected to be and the greater the power savings.

It is an advantage, in accordance with yet another feature of the invention, if the circuit configuration includes a device or means for detecting the transistor switching speed connected to the operational amplifier. With such a device, the transistor switching speed can be detected individually on the substrate so that the length of the common off-phases can be matched to the Q factor of the operational amplifier used.

It is then an advantage, in accordance with yet a further feature of the invention, if the switching speed of n-channel FETs and/or of p-channel FETs can be detected separately. The process for producing n-type FETs and p-type FETs includes completely different process steps. As such, it is possible that n-type FETs and p-type FETs located on the same substrate differ considerably with regard to their switching speeds.

Depending on the internal circuitry of an operational amplifier, its transient response may be mainly determined by the behavior of the n-type FETs or of the p-type FETs. In such a case, it is recommended to detect the switching speed
5 of the significant device type separately.

10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
22

inputs receiving an edge signal delayed through the inverter chain, and an XNOR gate with XNOR inputs, one of the XNOR inputs receiving an undelayed edge signal and another of the XNOR inputs receiving an edge signal delayed through the inverter chain.

Quite generally, it is an advantage, in accordance with yet an additional feature of the invention, if the device for detecting the transistor switching speed generates pulses, the duration of which characterizes the switching speed of the transistors. The duration of such pulses can be detected accurately with the aid of counter and timer chips and can be used as the basis for digital closed-loop control.

It is of advantage, in accordance with again another feature of the invention, to adjust the duration of the switching-clock phases in which all switching-clock signals are in the off-phase in dependence on the duration of the measuring circuit pulses. As the switching of the transistors becomes faster, the pulses occurring at the output of the measuring circuit become shorter and the on-phases that can be selected also become shorter. The common off-phases of the switching-clock signals can be correspondingly extended.

In accordance with again a further feature of the invention, the duration of the switching-clock phases in which all

switching-clock signals are in the off-phase can be adjusted in a number of predetermined steps. The embodiment is based on the concept that a large proportion of the power saving can be achieved already with a relatively coarse adjustment of the duration of the on-phases and of the common off-phase. As such, it makes sense to adapt the duration of the switching-clock phases in which all switching-clock signals are in the off-phase only in steps. The adaptation can be achieved with little circuit expenditure.

In accordance with again an added feature of the invention, the clock generator or means for clock generation and the device for varying the switching-clock phases in which all switching-clock signals are in the off-phase are preferably implemented by a programmable clock generator. In a programmable clock generator, the lengths of the individual switching-clock phases are represented digitally and are converted into corresponding switching-clock signals by counter and timer circuits. The duration of the individual switching-clock phases can be reprogrammed in a simple manner.

As an alternative, it is an advantage, in accordance with again an additional feature of the invention, if an external squarewave generator and a divider circuit implement the clock generator and the device for varying the switching-clock phases in which all switching-clock signals are in the off-

phase. In such a configuration, the divider circuit generates the at least two switching-clock signals from the squarewave signal. The generation makes it possible to find out with little external circuit expenditure what the magnitude of the spread of the transient response is with a certain filter or converter circuit and whether or not there is still potential for power saving. The duty ratio of the squarewave signal can be adjusted at the external squarewave generator. The common off-phase of the switching-clock signals can be varied by the duty ratio.

It is an advantage, in accordance with still another feature of the invention, if the circuit configuration is implemented in fully differential circuit technology. In mobile radio technology applications in particular, differential construction of the signal lines makes it possible to eliminate interference effectively.

With the objects of the invention in view, there is also provided a method for clocking successive operational amplifier stages constructed in switched op-amp technology, including the steps of generating at least two non-overlapping switching-clock signals, switching a first operational amplifier on and off with a first signal of the two switching-clock signals, switching a second operational amplifier on and off with a second signal of the switching-clock signals, and

varying switching-clock phases in which the operational amplifiers are switched off.

In the method according to the invention for clocking
5 successive operational amplifier stages constructed in
switched op-amp technology, at least two non-overlapping
switching-clock signals are generated in a first step, the
first switching-clock signal switching a first operational
amplifier on and off, and the second switching-clock signal
switching a second operational amplifier on and off. In a
second step, the phases of the switching-clock signals in
which all operational amplifiers are switched off are varied.

Introducing a controllable common off-phase makes it possible
to reduce the on times of the operational amplifier to the
necessary degree so that the power consumption of the circuit
can be restricted to a minimum.

In accordance with still a further mode of the invention, each
20 of the switching-clock phases in which the operational
amplifiers are switched off is varied.

In accordance with still an added mode of the invention, each
second one of the switching-clock phases in which the
25 operational amplifiers are switched off is varied.

In accordance with still an additional mode of the invention, a duration of the switching-clock phases in which the operational amplifiers are switched off dependent on a transient response of the operational amplifiers is varied.

5

In accordance with another mode of the invention, a duration of the switching-clock phases in which the operational amplifiers are switched off dependent on a switching speed of transistors of the operational amplifiers is varied.

In accordance with a further mode of the invention, at least one of a switching speed of n-channel FETs and a switching speed of p-channel FETs are separately detected.

In accordance with an added mode of the invention, at least one of a switching speed of n-channel FETs and a switching speed of p-channel FETs are separately detected.

In accordance with an additional mode of the invention, a duration of the switching-clock phases in which the operational amplifiers are switched off is adjusted in a number of predetermined steps.

In accordance with yet another mode of the invention, the non-overlapping switching-clock signals are generated with a programmable clock generator.

In accordance with yet a further mode of the invention, the non-overlapping switching-clock signals are generated with an external squarewave generator and a divider circuit.

5

In accordance with a concomitant mode of the invention, the switching-clock phases in which the operational amplifiers are switched off are varied by adjusting a duty ratio of a squarewave signal from the squarewave generator.

Other features that are considered as characteristic for the invention are set forth in the appended claims.

Although the invention is illustrated and described herein as embodied in a variable clock configuration for switched op-amp circuits, it is, nevertheless, not intended to be limited to the details shown because various modifications and structural changes may be made therein without departing from the spirit of the invention and within the scope and range of equivalents of the claims.

The construction and method of operation of the invention, however, together with additional objects and advantages thereof, will be best understood from the following description of specific embodiments when read in connection with the accompanying drawings.

Brief Description of the Drawings:

FIG. 1 is a schematic circuit diagram of a prior art circuit in switched op-amp technology including a number of
5 operational amplifier stages;

FIG. 2A is a block and schematic circuit diagram of a prior art circuit for generating a non-overlapping two-phase clock;

FIG. 2B is a timing diagram illustrating the input clock signal and the even and odd switching-clock signals generated by the circuit according to FIG. 2A;

FIG. 3 is a block circuit diagram of a clock generating unit according to the invention including a circuit for determining the transistor switching speed;

FIG. 4 is a block and schematic circuit diagram of an example circuit for determining the gate delay and the transistor
20 switching speed for use in the clock generating unit according to FIG. 3;

FIG. 5A is a timing diagram illustrating the input clock signal and the output signal of the circuit of FIG. 4 for a
25 case of short gate delays;

FIG. 5B is a timing diagram illustrating a variation with time of the even and odd switching-clock signals generated by the clock generating unit according to FIG. 3 for the case of short gate delays;

5

FIG. 6A is a timing diagram illustrating a representation of the input clock signal and of the output signal of the circuit shown in FIG. 4 for a case of long gate delays;

FIG. 6B is a timing diagram illustrating a variation with time of the even and odd switching-clock signals generated by the clock generating unit according to FIG. 3 for the case of long gate delays;

FIG. 7 is a schematic circuit diagram of a circuit providing for the separate determination of the switching speed of n-channel MOSFETs according to the invention; and

FIG. 8 is a timing diagram illustrating an overview of the clock signals of an external clock generating unit according to the invention in which the even clock signal and the odd clock signal are generated from a squarewave signal by a divider circuit.

25

Description of the Preferred Embodiments:

In all the figures of the drawing, sub-features and integral parts that correspond to one another bear the same reference symbol in each case.

5

Referring now to the figures of the drawings in detail and first, particularly to FIG. 1 thereof, there is shown a prior art switched op-amp circuit that includes two operational amplifier stages. The operational amplifier 1, the sampling capacitor 2, the integration capacitor 3, and the capacitor 4 form the first operational amplifier stage. The second operational amplifier stage includes the operational amplifier 5, the sampling capacitor 6, the integration capacitor 7, and the capacitor 8. The various switches shown in FIG. 1 are switched on and off by two non-overlapping switching-clock signals that will be called even and odd switching-clock signals in the text that follows. Before discussing the operation of the circuit shown in FIG. 1 in greater detail, the generation of these two switching-clock signals will be explained with reference to FIGS. 2A and 2B.

10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25

FIG. 2A illustrates a prior art clock generator for generating a non-overlapping two-phase clock. A rectangular input clock signal 21 having the frequency f_{clk} is applied to the input of the circuit. The variation with time of the input clock signal 21 is shown in FIG. 2B.

The input clock signal 21 is present, on one hand, at the input of the inverter 22 and also at an input of the second NOR gate 24. The output of the inverter 22 is connected to an input of the first NOR gate 23. At the output of the NOR gate 23, the output signal 25 is present that is delayed by the two inverters 26. At the output of the inverter chain, the even switching-clock signal 27 can be picked up, the variation with time of which is shown in FIG. 2B. The even switching-clock signal 27 is connected to the second input of the second NOR gate 24, at the output of which the output signal 28 appears. The output signal 28 is delayed by the two inverters 29 and, at the output of the inverter chain, the odd switching-clock signal 30 can be picked up, the variation of time of which is also shown in FIG. 2B. The odd switching-clock signal 30 is supplied to the second input of the first NOR gate 23.

The comparison of the variation of the even switching-clock signal 27 and of the odd switching-clock signal 30 by referring to FIG. 2B shows that the odd switching-clock signal 30 is in each case switched off during the on-phase of the even switching-clock signal 27. In addition, both switching-clock signals are in a common off-phase between the on-phase of the even switching-clock signal 27 and the on-phase of the odd switching-clock signal 30 during the period δ . It is, therefore, called a "non-overlapping two-phase clock".

Each of the switches shown in FIG. 1 is now switched on and off by the even switching-clock signal or by the odd switching-clock signal. Next to each switch, the switching clock by which it is clocked is noted.

Firstly, the first operational amplifier stage will now be considered during the on-phase of the even switching clock. The switches 9 and 10 are closed, therefore, whereas the switches 11, 12, 13 and 14 are open. The operational amplifier 1 is, therefore, inactive in such a phase. The input signal IN is present at one terminal of the sampling capacitor 2 and the other terminal is connected to VSS. The sampling capacitor 2 is, therefore, charged up by the input signal. The capacitor 4 is connected to VSS and VDD through the switches 9 and 10 and is, therefore, charged up by the supply voltage. The on-phase of the even switching-clock signal is followed - after a short common off-phase of both switching-clock signals - by the on-phase of the odd switching-clock signal. During such a phase, the switches 9 and 10 are open whereas the switches 11, 12, 13 and 14 are closed. Therefore, the operational amplifier 1 is switched on in the phase. One terminal of the sampling capacitor 2 is connected to VDD through the switch 12. The other terminal of the capacitor 2 is connected to the inverting input of the operational amplifier 1 through the switch 13. The capacitor

4 that is connected to VSS through the switch 14 in the phase additionally couples in a constant charge that produces a type of DC shift. The injected charge makes it possible to achieve an approximate potential VSS at the inverting input. The
5 operational amplifier 1, as the active component, now attempts to correct its output to such an extent that the difference between the input voltages becomes zero. Therefore, the operational amplifier 1 attempts to bring the inverting input to VSS potential. As a result, precisely the charge quantity that has been sampled at the sampling capacitor 2 is transferred to the integration capacitor 3.

The second operational amplifier stage is operated in the opposite phase to the first one. Still being considered is the on-phase of the odd switching clock in which the operational amplifier 1 is active. The switches 15 and 16 of the second op-amp stage are closed and that is why the output of the operational amplifier 1 charges up the sampling capacitor 6 belonging to the second operational amplifier
20 stage. Thus, the integration-phase of the first operational amplifier stage and the sampling phase of the second operational amplifier stage are taking place at the same time.

In the subsequent switching-clock phase, the charge quantity
25 sampled at the sampling capacitor 6 is transferred to the integration capacitor 7. During such integration-phase of the

second operational amplifier stage, the first operational amplifier stage is already back in the sampling phase.

The switching clock configuration shown in FIG. 2B is modified by the invention such that the on times of the operational amplifiers are shortened and, thus, a power saving is achieved. The hardware according to the invention is illustrated in FIG. 3. A programmable clock generator 31 is supplied with a squarewave input clock signal 32 having the frequency f_{clk} . A circuit 33 for determining the transistor switching speed determines the switching speed of the transistors that is significant for the transient response of the operational amplifiers. A pulse signal 34 characteristic of the switching speed is supplied to the programmable clock generator 31 and taken into consideration in the generation of the even switching-clock signal 35 and of the odd switching-clock signal 36. The faster the switching of the devices are, the shorter the on-phases of the operational amplifiers can be.

FIG. 4 illustrates an example for a circuit 33 for determining the transistor switching speed. The input clock signal 37 is present at the first input of the XOR gate 40. At the second input of the XOR gate 40, the delayed and inverted clock signal 39 is present that is obtained from the input clock signal 37 by an odd number of inversions (FIG. 4 shows three

inverters 38). If the input clock signal 37 is at 0, the signal 39 assumes the value 1 and the output signal 41 of the XOR gate 40 assumes the value 1. If the input clock signal 37 changes from 0 to 1, the new value 1 is immediately available at the first input of the XOR gate 40. The signal 39 only changes to the new value 0 after a certain time delay that is determined by the gate delay of the three inverters 38. During a period that is characteristic of the gate delay, the output signal 41 is, therefore, at 0 and then it assumes the value 1.

The duration of the pulses in the output signal 41 represents a measure of the switching speed of the transistors of the substrate. The measurement makes it possible to detect the effect of process spreads on the transistor switching speed directly on the chip and to take it into consideration during the clock generation. Instead of the XOR gate, an XNOR gate can also be used for determining the switching speed of the transistors.

FIG. 5A illustrates the variation with time of the input clock signal 37 and of the output signal 41 of the XOR gate 40.

When the input clock signal 37 changes from 1 to 0, a falling signal edge 42 is obtained that triggers a pulse 43 with a pulse width t_D in the output signal 41. During the pulse period t_D , the output signal 41 assumes the value 0.

When the input clock signal 37 changes from 0 to 1, a rising signal edge 44 is obtained that also triggers a pulse 45 of length t_D . The pulses 43, 45 shown in FIG. 5A are short and the corresponding values of t_D are low. Accordingly, the inverters 38 only produce a slight signal delay, which allows a high switching speed of the transistors and a short transient response of the operational amplifiers to be inferred.

The pulse signal 41 is supplied to the programmable clock generator that digitizes the period of the pulses 43, 45 and uses them for calculating the switching clock configuration. For the case of a short pulse duration t_D shown in FIG. 5A, the switching clock signals generated by the programmable clock generator, the even switching-clock signal 46, and the odd switching-clock signal 47 are shown in FIG. 5B. Because of the fast transient response of the operational amplifiers, only short on-phases 48, 49 are required.

The switching clock phases 50, 51, in which both switching-clock signals 46 and 47 are in the off-phase, can be correspondingly extended. In the prior art clock configuration shown in FIG. 2B, the common off-phases had the period δ . In the clock configuration shown in FIG. 5B, however, the duration of the common off-phases has been

increased to $\delta + t_a$. The operational amplifiers are only switched on until the transient is finished. During the common off-phases, all operational amplifiers are inactive.

5 FIG. 6A shows the input clock signal 52 and the output signal 53 of the XOR gate 40 for the case of transistors switching slowly or for long gate delays. The falling signal edge 54 causes a pulse 55 of duration t_D in the output signal 53 and the rising signal edge 56 correspondingly causes a pulse 57 of duration t_D . In the example shown in FIG. 6A, the transistors only have a low switching speed. The inverters 38, therefore, delay the signal considerably and the delay leads to a long pulse duration t_D , making it possible to infer a slow transient response of the operational amplifiers.

FIG. 6B shows the variation with time of the associated switching-clock signals, the even switching-clock signal 58 and the odd switching-clock signal 59. Because of the slow transient response of the operational amplifiers, the on-phases 60, 61 of the two switching-clock signals must be
20 selected to be long. Accordingly, the common off-phase 62 of the switching-clock signals must be reduced to the minimum period δ . Accordingly, t_a is set to be $= 0$.

The programmable clock generator maps the pulse duration t_D onto the duration of the common off-phase $\delta + t_a$, a small value of t_D being mapped onto a large value of $\delta + t_a$ and a large value of t_D being mapped onto a small value of t_a . As such, the switching clock configuration can be adapted to the switching speed of the transistors such that the power saving is at a maximum.

FIG. 7 illustrates an embodiment of the circuit 33 for determining the transistor switching speed that selectively detects the switching characteristic of n-type MOSFETs. The use of such a circuit is recommended if the transient response of the operational amplifiers used is mainly determined by the characteristics of the transistors of the n-type. The circuit includes the p-type MOSFETs 65, 66, 67 and the n-type MOSFETs 68, 69, 70, 71, 72, 73. The current through the FETs depends on the width/length ratio (W/L) of the respective FET. In the example illustrated in FIG. 7, the p-type FETs 65, 66, 67 and the n-type FETs 68, 69, 70 have a large W/L. The n-type FETs 71, 72, 73, the W/L ratio of which is much lower than that of the other devices, therefore, have a current-limiting effect.

When the input signal 63 changes to VSS, the p-type FET 65 is gated on. The gate of the n-type MOSFET 69 is then at VDD and, if VBIAS has been suitably selected, the n-type FET 72 is

also conducting. The potential VSS can then be switched through to the gate of the p-type FET 67. The p-type FET 67 places an input of the XOR gate 64 at VDD. Because of the low value of W/L in the case of the n-type FET 72, in comparison with the W/L values of the FETs 65, 67, 69, the total delay is essentially determined by the n-type FET 72. When the input signal 63 changes to VDD, in contrast, the total delay essentially depends on the switching speed of the n-type FETs 71 and 73. In every case, the total delay is, therefore, mainly determined by the n-type FETs having a small W/L.

FIG. 8 illustrates a method of how the clock configuration according to the invention can be generated externally by a squarewave generator and a divider circuit. The squarewave generator supplies a squarewave signal 74 having the frequency ($2 f_{clk}$). From the squarewave signal 74, the even switching-clock signal 75 and the odd switching-clock signal 76, which each have a period of $\frac{1}{f_{clk}}$, are derived by a divider circuit.

The duration of the common off-phase in which both switching-clock signals are equal to 0 can be adjusted by varying the duty ratio of the squarewave signal. The duty ratio of the squarewave signal 74 is 1/2 whereas the duty ratio of the squarewave signal 77 is 1/4. The squarewave signal 78 has a duty ratio of 3/4. The values of $\delta + t_a$ that belong to the

Conversely, a small duty ratio produces a distinct extension

Year	1970	1971	1972	1973	1974	1975	1976	1977	1978	1979	1980	1981	1982	1983	1984	1985	1986	1987	1988	1989	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100
1970	1971	1972	1973	1974	1975	1976	1977	1978	1979	1980	1981	1982	1983	1984	1985	1986	1987	1988	1989	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	